Terminal block type

Vseries



CE

2 directional terminal block system useful for installation


- Long range detection, 40 m through-beam type (universal voltage type)
- Types with built-in ON/OFF delay timer available









Detection of large package passage



Detection of metal can passage



Object detection when opening and closing roller shutters



Selection table

Туре		Shape	Sensing distance	Model (Types with timer functions shown in parentheses)	
Universal voltage	Through- beam		40 m	VT-4000 (VT-4000T)	
	Retro- reflective		0.01 to 10 m	VR-1000 (VR-1000T)	
	Diffuse- reflective		1.3 m	VD-130 (VD-130T)	
			3 m (infrared light)	VD-300 (VD-300T)	

	Туре	Shape	Sensing distance	Model (Types with timer functions shown in parentheses)	
туре		Snape	Sensing distance	NPN type	PNP type
DC power	Through- beam		30 m	VT-3000N	VT-3000P
	Retro- reflective		0.01 to 8 m	VR-800N	VR-800P
	Diffuse- reflective		1 m	VD-100N	VD-100P
			2.5 m (infrared light)	VD-250N	VD-250P

Options/Accessories

Reflector

Standard (included)

V-61

Sensing distance VR-800□: 0.01 to 8 m VR-1000□: 0.01 to 10 m





Universal voltage/Terminal block type

Universal voltage types are also available, eliminating the need to choose between voltages. Can be used with voltages around the world.




Universal voltage type ON delay OFF delay potentiometer potentiometer 24 to 240 VAC 12 to 240 VDC NO NC COM. Distance adjustment Output indicator

(power indicator for through-beam type emitter)

*ON delay potentiometer and OFF delay potentiometer are only equipped on models with timers

DC power type



Equipped with timer function

(Universal voltage type model equipped with timer)

Equipped with two timer functions. The OFF delay for extending the time until OFF and the ON delay for switching ON when detecting after more than a set period of time. The timer time can be set for between 0.1 and 10 seconds and the ON delay and OFF delay can be set at the same time.

Mirror surface detection (retro-reflective type)

Built-in polarizing filter for optical surfaces. Clearly differentiates between reflected light from the reflector and reflected light from the workpiece. Allows stable detection of mirror surfaces such as for plating and metal objects.







2-direction cable connection

On types with one-direction cable connections, it is necessary to be careful about the routing of the cable. With the V series, routing is possible from both the bottom and rear. This is a logical design that not only makes routing easy, but removes cable stress.





Laser Displacement Sensors

> Universal Voltage

> > V2

V3, V4

V

Specifications

Туре		Time	DC power type			
		туре	Through-beam type	Retro-reflective type	Diffuse-reflective type	
Model	NPN	No timer function	VT-3000N	VR-800N	VD-100N	VD-250N
		With timer function		_	-	
	PNP	No timer function	VT-3000P	VR-800P	VD-100P	VD-250P
	FINE	With timer function		_	-	
Sensing distance		istance	30 m	0.01 to 8 m ^{*1}	1 m*2	2.5 m ^{*3}
Light source		ce	Red LED Infrared LED			Infrared LED
Resp	onse	time	1.5 ms or less		5 ms or less	
Hysteresis		5	_	_ 20% or less		or less
Distance adjustment		adjustment	1-turn potentiometer (240°)			
Indic	ators		Output indicator (orange LED), Power indicators for through-beam type emitters (red LED)			
Control output		ıtput	NPN/PNP Open collector Max. 100 mA/30 VDC			
Output mode		ode	Light ON / Dark ON selection switch			
Test	input		Equipped			
Connection type		n type	Terminal block type (applicable cable outer diameter: ø6 to ø10 mm), Conduit : PF1/2 (JIS B0202)			
Insu	ation	resistance	20 MΩ or more (500 VDC)			
Rating	Supp	ly voltage	10 to 30 VDC, including 10% ripple (p-p)			
Ra	Curre	ent consumption	35 m		or less	
Appl	Applicable regulations		EMC directive (2004/108/EC)			
Appl	icable	standards	EN 60947-5-2			
Com	pany	standards	Noise resistance: Feilen Level 3 cleared			
la l		t temperature/humidity	-25 to +55°C (no freezing) / 35 to 85% RH (no condensation)			
Environmental resistance	Ambi	ent illuminance	Sunlight: 10,000 lx or less, Incandescent lamp: 3,000 lx			
onn ista	Vibra	tion resistance	10 to 55 Hz; double amplitude 1.5 mm; 2 hours in each of the X, Y, and Z directions			
nvir	Shoc	k resistance	Approx. 50 G (500 m/s²); 3 times in each of the X, Y, and Z directions			
Ш	Degre	ee of protection	IP67			
Material			Housing/Cover: ABS (glass fiber filled), Lens/Lens cover: PMMA			
Weight without cable		thout cable	Emitter: 70 g Receiver: 90 g	er: 70 g Receiver: 90 g 95 g		
Included accessories		accessories	Mounting bracket BEF-W260	Mounting bracket BEF-W260 Reflector: V-61	Mounting brac	ket BEF-W260

^{*1.} With the V-61 reflector



^{*2.} Using a 200 \times 200 mm white sheet of paper.

^{*3.} Using a 400×400 mm white sheet of paper.

[•] Specifications are subject to change without prior notice for product improvement purposes.

	T	Universal voltage type			
	Туре	Through-beam type Retro-reflective type Diffuse-reflective		ective type	
N 4	No timer function	VT-4000	VR-1000	VD-130	VD-300
Mod	With timer function	VT-4000T	VR-1000T	VD-130T	VD-300T
Sens	sing distance	40 m	0.01 to 10 m ^{*1}	1.3 m *2	3 m *3
Light source		Red LED Infrared LED			
Res	ponse time	20 ms or less			
Hyst	teresis	-	_ 20% or less		
Dista	ance adjustment	1-turn potentiometer (240°)			
Indicators		Output indicator (orange LED), Power indicators for through-beam type emitters (red LED)			
Only	types with timer functions	ON and OFF delay: 0.1 to 10 seconds			
Control output		Relay 1C ^{'4} 250 VAC 3 A or less, 30 VDC 3 A or less			
Output mode		Fixed to Light ON			
Connection type		Terminal block type (applicable cable outer diameter: ø6 to ø10 mm), Conduit : PF1/2 (JIS B0202)			
Insu	lation resistance	20 MΩ or more (500 VDC)			
Rating	Supply voltage	12 to 240 VDC, 24 to 240 VAC 50/60Hz			
Rat	Power consumption	8.5 VA		5 VA	
App	licable regulations	EMC directive (2004/108/EC), Low voltage directive (2006/95/EC)			
App	licable standards	EN 60947-5-2			
Com	npany standards	Noise resistance: Feilen Level 3 cleared			
	Ambient temperature/humidity	-25 to +55°C (no freezing) / 35 to 85% RH (no condensation)			nsation)
Environmental resistance	Ambient illuminance	Sunlight: 10,000 lx or less, Incandescent lamp: 3,000 lx			00 lx
vironment resistance	Voltage resistance		2700 VAC	.C / minute	
iror ssist	Vibration resistance	10 to 55 Hz; double amplitude 1.5 mm; 2 h		nours in each of the X, Y, and Z directions	
Env	Shock resistance	Approx. 50 G (500 m/s²); 3 times in		each of the X, Y, and Z directions	
	Degree of protection	IP67		67	
Material		Housing/Cover: ABS (glass fiber filled), Lens/Lens cover: PMMA			
Weight without cable		Emitter: 70 g Receiver: 90 g	g 95 g		
Included accessories		Mounting bracket BEF-W260	Mounting bracket BEF-W260 Reflector: V-61	Mounting brace	ket BEF-W260

^{*1.} With the V-61 reflector

- Specifications are subject to change without prior notice for product improvement purposes.
- Products certified for the Chinese CCC compulsory certification system also available. Contact us for details.

^{*2.} Using a 200 \times 200 mm white sheet of paper.

^{*3.} Using a 400 \times 400 mm white sheet of paper.

^{*4.} When driving the inductive load (with an induction valve, electromagnetic contactor, etc.) through the relay connection point, please use a noise absorption device (surge absorber).

Specialized Photoelectric Sensors

Laser Displacement Sensors

> Universal Voltage


> > V2

V3, V4


v

I/O circuit diagram

■ NPN output type (DC power type)




■ Through-beam type emitter (NPN. DC power type)



*PNP/DC power type emission stoppage is shorted with 10 to 30 VDC.

■ PNP output type (DC power type)




Connecting

■1 to 4 are connector pin No.


Notes

- ■When using a switching regulator for the power supply, be sure to ground the frame ground terminal.
- ■Avoid wiring in parallel with or in the same piping as high-voltage wires or power lines. Doing so may lead to malfunctions caused by noise. Also, shorten the power supply and signal wires as much as possible.
- ■Avoid using the transient state while the power is on (approx. 100 ms).

■ Universal voltage type



■ Through-beam type emitter (universal voltage type)






(Unit: mm)

Dimensions

Sensor with mounting bracket

■ Floor-mounted

Retro-reflective type/Diffuse-reflective type, Optical axis of emitter



■ Wall-mounted

Retro-reflective type/Diffuse-reflective type, Optical axis of emitter

